



MICRO-TECH SERIES

MT-1200

AC Power Draw and Thermal Dissipation

The information provided on this page is calculated data based on driving both channels to rated output using the 1 kHz Maximum Average Power rating method.

Other parameters used in calculation include a conservative idle current estimate of 90 watts and a conservative estimate of efficiency at 65%.

Information is provided only for getting an idea of current draw and heat produced. Actual performance will vary depending on environment, program material, load, signal, and AC mains voltage and frequency.

Values of calculated current draw are intended to represent average draw corresponding to the thermal breaker requirements that should be met to handle the amplifier as a load on the AC mains.

Peak current draw with dynamic program material may be significantly higher. Thermal information is provided to assist with calculating air conditioning needs. The data here should not be construed as specifications.

Duty cycle of various program material:

- Individual speech: 10%
- Acoustic/chamber music: 20%
- Full-range rock music: 30%
- Compressed rock music: 40%
- Pink noise: 50%

Here are the equations used to calculate the data presented in Figure 1:

$$\text{AC Mains Power Draw (watts)} = \frac{\text{Total output power with all channels driven (watts)} \times \text{Duty Cycle}}{\text{Amplifier Efficiency (.65)}} + \text{Quiescent Power Draw (watts)}$$

The quiescent power draw is a maximum value and includes power drawn by the fan. The following equation converts power draw in watts to current draw in amperes:

$$\text{Current Draw (amperes)} = \frac{\text{AC Mains Power Draw (watts)}}{\text{AC Mains Voltage} \times \text{Power Factor (.83)}}$$

The value used for Power Factor is 0.83. The Power Factor variable is needed to compensate for the difference in phase between the AC mains voltage and current. The following equation is used to calculate thermal dissipation:

$$\text{Thermal Dissipation (btu/hr)} = \left(\frac{\text{Total output power with all channels driven (watts)} \times \text{Duty Cycle} \times .35}{\text{Amplifier Efficiency (.65)}} + \text{Quiescent Power Draw (watts)} \right) \times 3.415$$

The value used for inefficiency is 1.00-efficiency. The factor 3.415 converts watts to btu/hr. Thermal dissipation in btu is divided by the constant 3.968 to get kcal. If you plan to measure output power under real-world conditions, the following equation may also be helpful:

$$\text{Thermal Dissipation (btu/hr)} = \left(\frac{\text{Total measured output power from all channels (watts)} \times .35}{\text{Amplifier Efficiency (.65)}} + \text{Quiescent Power Draw (watts)} \right) \times 3.415$$

Micro-Tech 1200

Duty Cycle	LOAD														
	2 Ohm Stereo / 4 Ohm Bridge					4 Ohm Stereo / 8 Ohm Bridge					8 Ohm stereo / 16 Ohm Bridge				
	AC Mains Power Draw (watts)	Current Draw (Amps)		Thermal Dissipation		AC Mains Power Draw (watts)	Current Draw (Amps)		Thermal Dissipation		AC Mains Power Draw (watts)	Current Draw (Amps)		Thermal Dissipation	
	120V	230V	btu/hr	kcal/hr		120V	230V	btu/hr	kcal/hr		120V	230V	btu/hr	kcal/hr	
50%	1128	11.4	5.7	1550	391	828	8.3	4.2	1190	300	567	5.7	2.9	880	222
40%	921	9.3	4.7	1300	328	681	6.9	3.4	1020	257	472	4.8	2.4	770	194
30%	713	7.2	3.6	1060	267	533	5.4	2.7	840	212	376	3.8	1.9	650	164
20%	505	5.1	2.6	800	202	385	3.9	2.0	660	656	281	2.8	1.4	540	136
10%	298	3.0	1.5	560	141	238	2.4	1.2	490	123	185	1.9	1.0	430	108



A Harman International Company
 Crown International, Inc.
 1718 W. Mishawaka Rd.
 Elkhart, IN 46517-9439
 TEL: 574-294-8200
 FAX: 574-294-8FAX
 www.crownaudio.com

For more details refer to the applicable Operation Manual or contact Crown Factory Service. The provided data should not be construed as specifications.
 Crown and Crown Audio® are registered trademarks of Crown international, Inc. Printed in U.S.A.
 ©2005 Crown Audio, Inc.