



Manufacturer: BSS Audio
 Model: BLU Series
 Device Type: Audio DSP

GENERAL INFORMATION

SIMPLWINDOWS NAME:	BSS BLU Preset Control Module v1.0
CATEGORY:	Audio DSP
VERSION:	v1.0
SUMMARY:	<p>This module is a control module for a suite of modules. The suite of modules utilizes the SIMPL# technology and will only work on the 3-Series Controller.</p> <p>The control modules are responsible for providing the actual control interface in SIMPL. With the SIMPL# technology, the Control modules no longer need to be physically "connected" to the command processor. They register themselves automatically behind the scenes. Each of the control modules also have a command processor ID parameter that you assign to the instance of the command processor to which they report to. You can virtually have an unlimited number of control modules report to a single instance of a command processor.</p> <p>The command processor must be initialized in order for this module to operate properly. Please see the BSS BLU Command Processor and BSS BLU RS232 Command Processor modules help files.</p>
GENERAL NOTES:	
CRESTRON HARDWARE REQUIRED:	3-Series Controller
SETUP OF CRESTRON HARDWARE:	N/A
VENDOR FIRMWARE:	This module was tested using BSS BLU Firmware Version: 86.02.02
VENDOR SETUP:	The SIMPL Demo program provided works with the also include BSS DSP Programming File: "BSS Crestron Demo.audioarchitect"
CABLE DIAGRAM:	This module does not communicate directly with the BSS DSP. Please see the BSS BLU Command Processor and BSS BLU RS232 Command Processor modules help files for connection information.

CONTROL:

<u>Signal/Function Name</u>	<u>D,S,A</u>	<u>Digital, Serial, Analog signal property definition.</u>
Select_Preset_*	D	Pulsing will recall the BSS parameter preset that has been assigned in the Preset_Value_* parameter field for the module.



Manufacturer: BSS Audio
 Model: BLU Series
 Device Type: Audio DSP

PARAMETERS:

CommandProcessorID	A	Set this value to match the value set on Command Processor module. This is how the control module registers itself for control.
Preset_Value_*	A	Assign the preset number to recall when pulsing the corresponding Select_Preset_* control signal.

TESTING: (please fill out carefully)

OPS USED FOR TESTING:	CP3 1.501.0025
SIMPL WINDOWS USED FOR TESTING:	4.05.03
DEVICE DB USED FOR TESTING:	79.05.002.00
CRES DB USED FOR TESTING:	59.00.002.00
SYMBOL LIBRARY USED FOR TESTING:	1012
SAMPLE PROGRAM:	BSS BLU v1.0 IP Demo.smw or BSS BLU v1.0 RS232 Demo.smw
REVISION HISTORY:	v1.0 – Initial Release