



## Processor Setting Chart

Processor: LAKE Contour  
Speaker Model(s): SRX712M  
Revision Date: 05/10/07

Northridge, CA 91329

### SRX712M Bi-Amp

OUTPUT	LOW1	LOW2	HIGH3	LOW4	LOW5	HIGH6
COMP/LIMIT						
LEVEL		0dB	-10 dB		0dB	-10 dB
LIMITER						
DELAY & POLARITY						
DELAY		0.21 ms	OFF		0.21 ms	OFF
POLARITY*		NORMAL	INVERT		NORMAL	INVERT
XOVER						
HP FREQUENCY		62.5Hz	1.73kHz		62.5Hz	1.73kHz
HP FILTER/SLOPE		BUT18	LR12		BUT18	LR12
LP FREQUENCY		1.0kHz	-		1.0kHz	-
LP FILTER/SLOPE		BUT18	-		BUT18	-
EQ						
F1 TYPE		BELL	BELL		BELL	BELL
F1 FREQUENCY		409Hz	2.00kHz		409Hz	2.00kHz
F1 GAIN		-2.6dB	-2.6dB		-2.6dB	-2.6dB
F1 WIDTH		0.66	0.5		0.66	0.5
F2 TYPE			BELL			BELL
F2 FREQUENCY			2.83kHz			2.83kHz
F2 GAIN			-2.8dB			-2.8dB
F2 WIDTH			.5			.5
F3 TYPE			BELL			BELL
F3 FREQUENCY			5.991kHz			5.991kHz
F3 GAIN			-3.0dB			-3.0dB
F3 WIDTH			1.2			1.2
F4 TYPE+			BELL			BELL
F4 FREQUENCY			15.5kHz			15.5kHz
F4 GAIN			+12.0 dB			+12.0 dB
F4 WIDTH			0.3			0.3

>using equal gain amplifiers