

Start code = 0  
 Implemented from CPU software version 0.3

# Exterior 600 DMX Protocol



CHANNEL		25 50 75 100 125 150 175 200 225 250														
L I G H T	1	SHUTTER closed   open		STROBE ←			B/O	RANDOM STROBE fast   med   slow			B/O	RESET *	B/O	LAMP ON	B/O	LAMP OFF* > 5 sec.
	2	DIMMER closed   open														
C O L O R	3	CYAN 0%   100% *														
	4	MAGENTA 0%   100% *														
	5	YELLOW 0%   100% *														
	6	CONTINUOUS COLOR SCROLL (0) white, DMX 0 (1) CTC, DMX 40 (2) red, DMX 80 (3) green, DMX 120 (4) blue, DMX 160										STEPS 4   3   2   1   0		CONTINUOUS ROTATION cw ←   ccw →		RND. COLOR f   m   s
B E A M	7	BEAM SHAPER 0° (open)   90°   FROST														
	8	ZOOM flood   spot														
S P E E D	9 (mode 2 only)	EFFECTS SPEED														
		dimmer, CMY, zoom ←										Ts   Tf   f		Ts   Tf   «»		
		color wheel, beam shaper ←														

\* Set CMY from 230 to 232 to override disabled function.  
 T = tracking mode (0-2 & 246-251)  
 S = shortcuts off (246-248)  
 F = shortcuts on (249-251)  
 «» = blackout speed (252-255)  
 ← = variable speed, points to fast