

# dmx512 interface



The AXB-DMX512 Interface acts as an intelligent bi-directional DMX512 to AXLink interface, transmitting and receiving up to 512 DMX channels for lighting dimmers, spotlights, and other DMX control applications.

An intelligent interface, the AXB-DMX512 contains onboard processing and memory. DMX channels can be grouped, soft-patched, or assigned to a fader. Up to 72 presets (284 presets with added memory) can be stored and recalled from internal memory.

A DMX lighting board can operate in tandem with the AXB-DMX512, generate levels for storing internal presets, or bypass the interface for direct control of channels. The board's channel commands will not be affected by AXB-DMX512 channel patches or groupings.

The AXB-DMX512 can be extended up to 3,000 feet using the AXLink data/power bus. The optional AC-RK Accessory Rack Kit is available for rack mounting.



# dmx512 interface

## AXB-DMX512 (FG5972)

- Generates DMX512 data signals (data stream software adjustable from 1 to 512 channels)
- Receives DMX commands from a USITT DMX lighting console or other sources
- Stores channel groups, patches, and up to 72 presets in non-volatile onboard memory, 284 with optional extended memory (EXM-256KB)
- Assigns channels to as many as 8 groups as well as attaches both channels and groups to up to 8 faders
- Operates in tandem with DMX lighting board (highest level has precedence)
- Provides bypass mode to allow direct control from a lighting board or DMX source
- Re-transmits DMX data from external sources without affecting the source's channel grouping or patches
- Extends control up to 3,000 feet via the AXLink data/power bus
- Mounts in equipment rack with optional AC-RK Accessory Rack Kit

## FRONT PANEL

AXLink: Green LED lights to show status of AXLink communication and DC power

Device: 8-position device assignment DIP switch

TX: Red LED lights when transmitting DMX data

RX: Red LED lights when receiving DMX data

## REAR PANEL

In: 6-pin DMX In jack

Out: 6-pin DMX Out jack

AXLink: 4-pin jack for AXLink data/power bus

## ENCLOSURE

- Metal with black matte finish

## DIMENSIONS (HWD)

- 1.51" x 5.55" x 5.45" (38.4 cm x 14.10 cm x 13.84 cm)

## WEIGHT

- 1.1 lbs (513.0 g)

## POWER


- 12 VDC at 160 mA

## INCLUDES


- One 4-pin AXLink connector
- Two 6-pin DMX connectors

## OPTIONS


- AC-RK Accessory Rack Kit
- EXM-256KB Extended Memory



AXB-DMX512 (front)



AXB-DMX512 (rear)



AXB-DMX512 (top)



IT'S YOUR WORLD. TAKE CONTROL.

ARGENTINA • AUSTRALIA • BELGIUM • BRAZIL • CANADA • CHINA • ENGLAND • FRANCE • GERMANY • GREECE • HONG KONG • INDIA • INDONESIA • ITALY • JAPAN  
 LEBANON • MALAYSIA • MEXICO • NETHERLANDS • NEW ZEALAND • PHILIPPINES • PORTUGAL • RUSSIA • SINGAPORE • SPAIN • SWITZERLAND • THAILAND • TURKEY • USA  
 ATLANTA • BOSTON • CHICAGO • CLEVELAND • DALLAS • DENVER • INDIANAPOLIS • LOS ANGELES • MINNEAPOLIS • PHILADELPHIA • PHOENIX • PORTLAND • SPOKANE • TAMPA  
 3000 RESEARCH DRIVE, RICHARDSON, TX 75082 • 800.222.0193 • 469.624.8000 • +1.469.624.7400 • 469.624.7153 fax • www.amx.com