

Error Codes/messages for FDS355, LMS626 and OEM units
 13 January 1998

| | |
|---------------------|---|
| "Nothing wrong! ", | No error |
| "No more filters ", | No more filters available |
| "Recall failed ", | Requested program not found e.g. midi program recall |
| "MIDI tx buf full", | Midi transmit buffer full |
| "Power Failure ", | One or more power lines out of spec |
| "%2x Modes fixed ", | At power up, data errors found |
| "Assert Failed x ", | Debug message - should not appear on production machine |
| "Watchdog Fail x ", | Software has failed and stopped |
| "Midi dump error ", | not used |
| "Midi in error ", | Error in incoming midi dump |
| ****Receiving****", | Receiving Midi Dump - certain types |
| "Password wrong ", | Wrong password entered |
| "Test failed ", | Test failed |
| "Test Completed ", | Test completed |
| "DRAM FAIL DSP%2x", | DRAM test failed |
| "OEM Locked ", | Tried to overwrite OEM program |
| "Delays too long ", | Input and output delays added to more than 1.3s |
| "All Flat ", | not used |
| "Bad card ", | not used |
| "Bad Format ", | Doesn't recognise card format |
| "Formatting ", | Formatting |
| "Bad card write ", | Can't write byte to card (card missing or bad card) |
| "No space on card", | Ran out of card space |
| "File is missing ", | Can't find requested file (card removed?) |
| "File error ", | Bad card problems (damaged file block etc) |
| "Checksum error ", | Bad file (read from card) |
| "There is no card", | No card in slot |
| "Write protected ", | Card is write protected |
| "No BSSDATA dir ", | Card does not have BSSDATA subdirectory in root |
| "File read error ", | not used |
| "Battery Low ", | not used |
| "Cal FAILED ", | not used |
| "Cal complete ", | not used |
| "Finished ", | not used |
| "Sending system ", | not used |
| "Sending progs ", | not used |
| "Received system ", | not used |
| "Received progs ", | not used |

| | |
|---------------------------|--|
| "Excessive errors", | not used |
| "Data checked ", | Bad data in flash change block storage |
| "Card port passed", | not used |
| "Card battery low", | Card Battery flat |
| "Dump time out ", | Dump has taken too long and has not finished correctly |
| "Delete failed ", | not used |
| "DSP recovering ", | not used |
| "MIDI Comms Error", | Midi checksum error on incoming midi dump |
| "Incoming dump ", | not used |
| "Program locked ", | Trying to overwrite program locked program |
| "No storage space", | Not much program storage space left |
| "DSP Error 1 ", | Illegal command to DSP |
| "DSP Error 2 ", | DSP receiver or transmitter overrun |
| "DSP Error 3 ", | DSP comms has timed out (no reply from dsp) |
| "DSP Error 4 ", | Block move error in dsp |
| "Data copied to Backup", | Data copied to backup (backup/swap is on) |
| "No Data in Backup", | Havent stored anything in Backup yet (backup/swap is on) |
| "Listening to Backup", | Now listening to backup (backup/swap is on) |
| "Listening to Edit", | Now listening to edit (backup/swap is on) |
| "Set Trims to Zero", | Recalling a program with Store Gains on |
| "Further EQs are locked", | Further EQs have been locked out by OEM |